



**Europäisches  
Patentamt**

**European  
Patent Office**

**Office européen  
des brevets**

1c542 U.S. PTO

09/629109



**Bescheinigung**

**Certificate**

**Attestation**

Die angehefteten Unterlagen stimmen mit der ursprünglich eingereichten Fassung der auf dem nächsten Blatt bezeichneten europäischen Patentanmeldung überein.

The attached documents are exact copies of the European patent application described on the following page, as originally filed.

Les documents fixés à cette attestation sont conformes à la version initialement déposée de la demande de brevet européen spécifiée à la page suivante.

**Patentanmeldung Nr.    Patent application No.    Demande de brevet n°**

99115675.3

Der Präsident des Europäischen Patentamts;  
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets  
p.o.

**I.L.C. HATTEN-HECKMAN**

DEN HAAG, DEN  
THE HAGUE,    25/05/00  
LA HAYE, LE

**THIS PAGE BLANK (USPTO)**



Europäisches  
Patentamt

European  
Patent Office

Office européen  
des brevets

**Blatt 2 der Bescheinigung**  
**Sheet 2 of the certificate**  
**Page 2 de l'attestation**

Anmeldung Nr.:  
Application no.: 99115675.3  
Demande n°:

Anmeldetag:  
Date of filing: 09/08/99  
Date de dépôt:

Anmelder:  
Applicant(s):  
Demandeur(s):  
DEUTSCHE THOMSON-BRANDT GMBH  
78048 Villingen-Schwenningen  
GERMANY

Bezeichnung der Erfindung:  
Title of the invention:  
Titre de l'invention:

Method for fast Fourier transformation of audio signals

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:  
State:  
Pays:

Tag:  
Date:  
Date:

Aktenzeichen:  
File no.  
Numéro de dépôt:

Internationale Patentklassifikation:  
International Patent classification:  
Classification internationale des brevets:

G06F17/14, H04B1/66

Am Anmeldetag benannte Vertragsstaaten:  
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE  
Etats contractants désignés lors du dépôt:

Bemerkungen:

Remarks:  
Remarques: See for original title of the application  
page 1 of the description.

**THIS PAGE BLANK (USPTO)**

- 1 -

## Method and encoder for bit-rate saving encoding of audio signals

The invention relates to a method and an encoder for bit-rate saving encoding of audio signals, especially for encoding of audio signals according to MPEG 1 Audio Layer II.

### Prior art

10

The MPEG 1 Audio standard as specified in ISO/IEC 11172-3 defines three operational modes known as Layers I, II and III. Each Layer offers increased compression but also increased encoding complexity, whereby downward compatibility is guaranteed. Therefore, a Layer II decoder can also read a Layer I data stream but no Layer III data stream. Also a Layer III decoder can decode all MPEG 1 Audio bit streams, i. e. Layer I to III.

20

MPEG 1 Audio data compression is based on subband coding. The audio signal is split into 32 subbands of equal width. A quantization is performed using a psychoacoustic model that is adapted to the masking behaviour of the human hearing. Each subband signal is quantized in such a way that the quantization noise introduced by the coding will not exceed the masking curve for that subband. After quantization the samples build - together with the scale factors and further coding information - a frame structure for transmission.

30

In ISO/IEC 11172-3 two independent psychoacoustic models are defined which can be adapted to any Layer. The output from these psychoacoustic models is a set of Signal-to-Masking Ratios,  $SMR_n$ , for every subband n.

In order to calculate the  $SMR_n$  for the psychoacoustic model 2 a Fast Fourier Transformation (FFT) with a length of 1024 samples is used, which has to run two times per channel, i. e. four times for a stereo channel.

# Invention

10 The invention is based on the object of specifying a method for bit-rate saving encoding of audio signals using a psychoacoustical model with reduced computing power. This object is achieved by means of the method specified in claim 1.

15

It is a further object of the invention to disclose an encoder which utilises the inventive method. This object is achieved by the apparatus disclosed in claim 6.

20 The invention is based upon the following realization. On the one hand a FFT is a special discrete Fourier Transformation for which the number of samples has to be a power of two, e.g. 1024 samples. However, on the other hand the frame length of MPEG 1 Audio Layer II is 1152  
 25 samples which is no power of two. This results in the two runs per channel of the FFT according to prior art.

The known formula for a discrete Fourier Transformation, which calculates for L elements of a data series  $z(n)$  the  
 30 corresponding L frequency values  $F(m)$ ,

$$F(m) = \frac{1}{L} \sum_{n=0}^{L-1} z(n) \exp(-j2\pi \frac{mn}{L})$$

can be transformed first into k partial sums with M  
 35 summands each

09-08-1999

PD990060 - RI - 09.00.1999

EP99115675.3

SPEC

- 3 -

$$F(m) = \frac{1}{L} \sum_{i=0}^{k-1} \left[ \sum_{n=0}^{M-1} z(kn+i) \exp(-j2\pi \frac{m(kn+i)}{L}) \right]$$

and finally with  $L=kM$  and splitting the exponential  
5 function into

$$F(m) = \frac{1}{k} \sum_{i=0}^{k-1} \left[ \frac{1}{M} \sum_{n=0}^{M-1} z(kn+i) \exp(-j2\pi \frac{mn}{L}) \right] \exp(-j2\pi \frac{mi}{L}).$$

Therefore, using  $k$  subtransformations with a length of  
10  $M=2^N$  allow time effective calculation with Fast Fourier  
Transformations, even if  $L$  is not a power of two.

In principle, the method for bit-rate saving encoding of  
audio signals using a psychoacoustic model, wherein a  
15 Fourier Transformation is performed for calculation of a  
minimum masking threshold and wherein  $L$  samples of the  
audio signal are arranged in a frame for transmission,  
consists in the fact that the Fourier Transformation is  
performed with a length of  $L$  samples by calculating  $k$   
20 subtransformations over  $2^N$  samples with  $k \cdot 2^N = L$  and fitting  
together the results of the  $k$  subtransformations.

In this way, the duplicate run per channel is avoided  
without lost of information or introduction of errors.  
25 Therefore, the computing power is reduced nearly to the  
half. This is especially important for the implementation  
on digital signal processors to run in real time.

Although the inventive method is especially advantageous,  
30 if the number  $k$  of subtransformations is not a power of 2,  
the use of the invention is not restricted to such values  
of  $k$ .

09-08-1999

EP99115675.3

SPEC

PD990060 - R1 - 09.08.1999

- 4 -

Advantageously, before fitting together the results of the  $k$  subtransformations, these are multiplied with phase correction factors.

- 5 In an advantageous manner, the Fourier Transformation is performed within the algorithm for the psychoacoustic model 2 of MPEG I Audio Layer II, wherein the frame length  $L$  is 1152 samples.
- 10 In an advantageous development  $k=9$  subtransformations with a length of  $M=2^N = 128$  samples are calculated.

#### Drawing

15

Exemplary embodiments of the invention are described with reference to the figure, which shows schematically the use of the subtransformations.

20

#### Exemplary embodiments

- Although the encoder is not standardized in ISO/IEC 11172-3, certain means for encoding such as the estimation of
- 25 the masking threshold or quantization are commonly used and therefore are not described in detail in the following. First of all PCM audio samples with a sampling frequency of 32, 44.1 or 48 kHz (or with half sample frequencies of 16, 22.05 or 24 kHz) are fed into the
- 30 encoder. A mapping is performed to create a filtered and subsampled representation of the input audio stream in the form of so-called subband samples. Each subband signal is quantized in such a way that the quantization noise introduced by the coding will not exceed the masking curve
- 35 for that subband. In order to control the quantization a



09-08-1999

EP99115675.3

PD990060 - Ri - 09.08.1999

- 5 -

psychoacoustic model is used to calculate the new bit allocation, for MPEG 1 Audio Layer II for three blocks totaling 36 subband samples corresponding to 1152 input PCM samples. The calculation is based on the Signal-to-Masking Ratios,  $SMR_n$ , for all the subbands, which makes it necessary to determine for each subband the maximum signal level and the minimum masking threshold. The minimum masking threshold is derived by using the inventive method which is schematically shown in Fig. 1. After windowing the input PCM samples, samples corresponding to a frame F1 are split and fed to nine subtransformation ST1, ..., ST9. Each subtransformation has a length of 128 samples ( $9 \cdot 128 = 1152$ ) which is the seventh power of 2 ( $2^7 = 128$ ). After Fast Fourier Transformations of the partial signals the results of the nine subtransformations are multiplied with phase correction factors, symbolized by multiplier units M1, ..., M9. The phase corrected data are combined, symbolized by adder unit A and then used for the further calculation of the psychoacoustic model. The same method is applied to the following audio samples corresponding to frames F2, F3 etc.

The invention can advantageously be used for encoding of audio signals according to MPEG 1 Audio Layer 2, but also applies to the encoding of any other kind of digital data.

The invention can be implemented in any kind of encoders which can be used e.g. for Digital Audio Broadcast (DAB), Cable and satellite radio/TV or digital recording devices like DVD-VRs etc.

09-08-1999

EP99115675.3

SPEC

PD990060 - R1 - 09.08.1999

- 6 -

Patent Claims

1. Method for bit-rate saving encoding of audio signals  
using a psychoacoustic model, wherein a Fourier  
5 Transformation is performed for calculation of a  
minimum masking threshold and wherein L samples of the  
audio signal are arranged in a frame (F1, F2, F3) for  
transmission, characterized in that the Fourier  
Transformation is performed with a length of L samples  
10 by calculating k subtransformations (ST1,..., ST9) over  
 $2^N$  samples with  $k \cdot 2^N = L$  and fitting together (A) the  
results of the k subtransformations.
2. Method according to claim 1, wherein the number k of  
15 subtransformations is not a power of 2.
3. Method according to claim 1 or 2, wherein before  
fitting together the results of the k  
subtransformations, these are multiplied with phase  
20 correction factors (M1,..., M9).
4. Method according to any of claims 1 to 3, wherein the  
Fourier Transformation is performed within the  
algorithm for the psychoacoustic model 2 of MPEG I  
25 Audio Layer II and wherein the frame length L is 1152  
samples.
5. Method according to claim 4, wherein  $k=9$   
subtransformations with a length of  $M=2^N = 128$  samples  
30 are calculated.
6. Encoder for performing the method according to claim 1.

1/1




Fig. 1

09-08-1999

PD990060 - 12 - 09.08.1999

EP99115675.3

SPEC

- 7 -

Abstract

MPEG 1 Audio data compression is based on subband coding. A quantization is performed using a psychoacoustic model which is adapted to the masking behaviour of the human hearing. Each subband signal is quantized in such a way that the quantization noise introduced by the coding will not exceed the masking curve for that subband. In ISO/IEC 11172-3 two independent psychoacoustic models are defined. The output from these psychoacoustic models is a set of Signal-to-Masking Ratios,  $SMR_n$ , for every subband  $n$ . In order to calculate the  $SMR_n$  for the psychoacoustic model 2 according to the invention a Fast Fourier Transformation (FFT) is performed with a length of  $L=1152$  samples by calculating  $k$  subtransformations ( $ST_1, \dots, ST_9$ ) over  $2^N$  samples with  $k \cdot 2^N = L$  and fitting together (A) the results of the  $k$  subtransformations.

20 Fig. 1